

# **Development of Radiation Hard Sensors**

Gunnar Lindström, University of Hamburg

And

On behalf of the CERN-RD48 (ROSE) Collaboration

## **OUTLINE**

- ◆ **Semiconductor detector materials**

**General remarks**

**Properties**

**Examples**

- ◆ **Development of rad hard silicon detectors – Results from CERN-RD48**

**DOFZ silicon – macroscopic results**

**Annealing Studies & Hamburg model**

**LHC-projections**

**Microscopic understanding**

**Open questions**

- ◆ **Conclusions**

# Possibilities for Improving the Radiation Tolerance of Tracking Detectors for HEP Experiments


- ◆ Selection of Detector Material ←
- ◆ Detector Design (guard rings, 3D design,.....)
- ◆ Defect Engineering (impurities)
- ◆ Operational Conditions (cooling,....)

# Criteria for Semiconductor Tracking Detectors

- ◆ Bandgap larger than Silicon  
(Si: 1.12 eV) ⇒ less cooling necessary
- ◆ Bandgap smaller than Diamond  
(C: 5.46 eV) ⇒ lower ioniz. energy ⇒ good S
- ◆ Large Radiation Length ≈ Silicon  
(Si: 9.4 cm) ⇒ stable wafer thickness
- ◆ High e/h-mobilities ≥ Silicon  
(Si: 1400/450 cm<sup>2</sup>/Vs) ⇒ fast charge collection
- ◆ Low dielectric constant < Silicon  
(Si: 11.7) ⇒ low capacitance ⇒ low N
- ◆ Low trap concentration, monocrystalline  
(Si: ≈ ideal) ⇒ good charge collection
- ◆ Large displ. energy for PKA ≥ Silicon  
(Si: 21 eV) ⇒ less rad. damage ⇒ stable S/N
- ◆ Mechanical strength & heat conductance ⇒ good for process handling  
stability as detector component
- ◆ Commercial product, standard process ⇒ large scale use, cost effective

[S = signal height for mip's, N = noise]

## A closer look at the bandgap



**Ionization energy vs. bandgap energy**  
(from Dubbs et al., IEEE 98)

	band gap [eV]	w/ehpair [eV]	R.Length $X_0$ [cm]	eh-pairs/ 0.3% $X_0$
Ge	0.76	2.9	2.3	17 E3
Si	1.12	3.6	9.4	30 E3
InP	1.34	4.3	2.1	8.9E3
GaAs	1.42	4.2	2.3	10 E3
CdZnTe	1.5-2.2	5-7	?	?
SiC	2.9	9.3	8.1	16 E3
C(diamond)	5.46	13	18.8	7.2E3

0.3% $X_0$  for Si = 280  $\mu\text{m}$

However optimization needed since:

- ◆ Low bandgap  $\Rightarrow$  low w but high current
- ◆ High bandgap  $\Rightarrow$  low current (SI!!) but small S


## Electrical Properties – Some examples

	$\epsilon$	$E_{\text{break-down}}$ [V/cm]	$\mu_e$ [cm <sup>2</sup> /Vs]	$\mu_h$ [cm <sup>2</sup> /Vs]	$v_{\text{saturation}}$ [cm/s]	Thermal conductivity [W/cmK]
<b>Si</b>	11.9	$3*10^5$	1350	480	$8*10^6$	1.5
<b>InP</b>	12.5	$5*10^5$	5400	200	$3*10^7$	
<b>GaAs</b>	13.1	$4*10^5$	8500	400	$8*10^6$	0.45
<b>SiC</b>	9.7	$2*10^6$	900	20	$2*10^7$	4.9
<b>C</b>	5.7	$10^6-10^7$	1800	1200	$2*10^7$	15

- ◆ Charge carrier mobilities depend on electric field and temperature, decreasing with increasing E and decreasing T, values are given for T=293K and zero (low) field
- ◆ The charge collection time  $t_c$  depends on the carrier type, the smaller  $\mu$ -value governs the minimum achievable value. For low E  $t_c = d^2/(\mu * V)$ , for high E look at details of transport properties
- ◆ Charge collection efficiency governed by  $\mu\tau$ -product with  $\tau$  = lifetime of e resp h-carriers.  
Main problems:  
Crystalline imperfections (diamond), stoichiometry (abundance of one constituent in compounds)  
Impurities acting as deep traps (also intentionally for compensation), polarization effects at surface

# NIEL governed radiation damage


## Comparison between Si and GaAs as example



monocrystalline, ideal  
large  $X_0$   
larger  $S(\text{nfp}/X_0)$   
ideal charge collection  
has to be cooled!

Si

Displacement  
energy = 21 eV



large band gap  
usable at RT  
"faster" than Si  
not ideal ch. collection  
(deep traps)  
worse rad. damage than Si

GaAs

Displacement  
Energy = 10 eV

Curves taken from M.Rogalla,  
PhD thesis 1997


◆ The damage in GaAs at high proton  
energies is ~~1.5~~ x larger than in Si

10


Reason: nuclear  $\sim$  larger  
more reaction channels  
 $\rightarrow$  lower energies of residuals

# Development of CdZnTe strip detectors - Example



(taken from O. Tousignant et al., University of Montreal and University of New Hampshire, Space Science Center)



Small segment of the prototype strip detector.



However:  
promising  
material  
for  
limited applications



$\mu \cdot \tau$  - problem

$$\mu_e \tau_e = 55 \cdot 10^{-6}$$

$$\mu_{h} \tau_h = 48 \cdot 10^{-6}$$

$$E \approx 10^3 \text{ V/cm}$$

$$t_C/\tau \approx 1 \text{ for } d = 300 \mu\text{m}$$

	Mobility $\text{cm}^2 \text{V}^{-1} \text{s}^{-1}$	Trapping Time	Detrapping Time
Electrons	1000	55 ns	28 ns
Holes	15	3.2 $\mu\text{s}$	> 50 $\mu\text{s}$

Silicon in comparison:

$$\tau \approx 1 \text{ ms}$$

$$M \cdot \tau \approx 1$$

$$E \approx 10^4 \text{ V/cm}$$


$$t_C/\tau \approx 3 \cdot 10^{-6}$$

$$\text{for } d = 300 \mu\text{m}$$

TRAPPING

# CVD Diamond as material for strip and pixel detectors





(example: CERN-RD42 Collaboration)




## Virtues:

"fastest" semiconductor  
large  $X_0$ , low  $\epsilon$   
large bandgap, usable @ RT  
high radiation tolerance

Problems:  
polycrystalline  $\rightarrow$  trapping  
limited charge collection eff.  
polarization effects  
cost ?




# Oxygen and Carbon - the key ingredients -



◆ **DOFZ – Diffusion oxygenated Float Zone**  
Controlled introduction of oxygen,  
easily included in manufacturing process, low cost

# Oxygen diffusion



## ◆ DOFZ – Diffusion oxygenated Float Zone



Open question:

Diffusion time/oxygen concentration needed to get the beneficial effect?

For the moment:

16 h diffusion at 1150°C ( $[O] = 1.5 \times 10^{17} \text{ cm}^{-3}$ ) seems to be sufficient

# Leakage Current – Annealing




- ◆ Oxygenated and Standard Silicon show same annealing
- ◆ Damage parameter  $\alpha$  :  $\alpha = \frac{\Delta I}{V \cdot \Phi_{eq}}$  independent of  $\Phi_{eq}$   
used for fluence (NIEL) calibration !

# $N_{\text{eff}}$ - effective doping concentration


$$|N_{\text{eff}}| \propto \frac{V_{\text{dep}}}{d^2}$$

- positive – n-type silicon (e.g. Phosphorus doped - Donor)
- negative – p-type silicon (e.g. Boron doped – Acceptor)
- $|N_{\text{eff}}|$  proportional to depletion voltage and  $1/(\text{device thickness})^2$



# Oxygen and standard silicon - Particle dependence -


24 GeV/c protons - 192 MeV pions - reactor neutrons



- ◆ Strong improvement for pions and protons
- ◆ No improvement for neutrons

# Influence of Carbon and Oxygen concentration

24 GeV/c proton irradiation




Compared to standard silicon:


- ◆ High Carbon  $\Rightarrow$  less radiation hard
- ◆ High Oxygen  $\Rightarrow$  radiation harder

# Influence of initial resistivity on oxygen rich material

24 GeV/c proton irradiation



Reactor neutron irradiation




- ◆ Measured after annealing equivalent to 10 days at room temperature
  - ◆ Low resistivity material beneficial for neutron irradiation

# Annealing behavior: $N_{\text{eff}}$

- Hamburg Model -

$$\Delta N_{\text{eff}}(\Phi_{\text{eq}}, t) = N_{\text{eff}0} - N_{\text{eff}}(\Phi_{\text{eq}}, t)$$

Change of  $N_{\text{eff}}$  with respect to  $N_{\text{eff}0}$   
(value before irradiation) :



$$\Delta N_{\text{eff}}(\Phi_{\text{eq}}, t) = N_a(\Phi_{\text{eq}}, t) + N_C(\Phi_{\text{eq}}) + N_Y(\Phi_{\text{eq}}, t)$$

short term annealing:

$$N_a = \Phi_{\text{eq}} \times \sum_i g_{ai} \times \exp\left(-\frac{t}{\tau_i}\right)$$

first order decay of acceptors  
introduced proportional to  $\Phi_{\text{eq}}$   
during irradiation

stable damage:

$$N_C = N_{C0} \cdot \left(1 - \exp\left(-c \cdot \Phi_{\text{eq}}\right)\right) + g_C \cdot \Phi_{\text{eq}}$$

incomplete „donor removal“  
+ introduction of stable acceptors

long term reverse annealing:

$$N_Y = N_{Y,\infty} \cdot \left(1 - \frac{1}{1 + t/\tau_y}\right)$$


second order parameterization  
(with  $N_{Y,\infty} = g_Y \times \Phi_{\text{eq}}$ ). gives best fit

But:

$\tau_y$  independent of  $\Phi_{\text{eq}}$   
 $\Rightarrow$  underlying defect reaction  
based on **first order** process!

# Systematic analysis of annealing data


Example: oxygen enriched silicon after neutron irradiation






S05B-ANNEAL-P | 19.3.2000

# Systematic analysis of annealing data

Example: oxygen enriched silicon after proton irradiation





# Extraction of damage parameters




- ◆ neutron irradiated  
O-rich diodes
- ◆ Extracted parameters  
independent of  
annealing temperature  
( $60^\circ\text{C}, 80^\circ\text{C}$ )

# Extraction of damage parameters




- ◆ proton irradiated  
O-rich diodes
- ◆  $g_c$  improved by a factor of 3
- ◆ saturation of reverse annealing
- ◆ delayed reverse annealing



# Suppression of Reverse Annealing in O-enriched Si-strip detectors

An important result from MPI Munich confirming the ROSE predictions

CiS-detectors, 2-5 k $\Omega$ cm, irrad. by  $3\text{e}14 \text{ p/cm}^2$  at  $-10^\circ\text{C}$ , 100V bias  
(data from L. Andricek and G. Lutz, MPI Munich)



MPI-DATA | 1.6.2000

Gunnar Lindström, Universität Hamburg + CERN-RD48, PIXEL 2000, Genoa 05-09 June 2000

# Comparison: $C_s/V$ and CCE/V

- proton irradiated oxygenated silicon -

## CCE measurement:

TCT - 830nm,  
front illumination

$t_{\text{ann}} = 8 \text{ min at } 80^\circ\text{C}$


$V_{\text{dep}} (\text{C/V}) = 56 \text{ V}$

$V_{\text{dep}}(\text{CCE/V}) = 55 \text{ V}$

$t_{\text{ann}} = 960 \text{ min at } 80^\circ\text{C}$

$V_{\text{dep}} (\text{C/V}) = 260 \text{ V}$

$V_{\text{dep}}(\text{CCE/V}) = 258 \text{ V}$




◆  $V_{\text{dep}}$ : Coincidence between CV and CCE

◆ However: CCE(V) depends on both:  $V_{\text{dep}}$  and trapping !


# CCE/V measurements

- proton irradiated oxygenated silicon -  
- TCT with 835nm laser (front illumination) -

8 min at 80°C




960 min at 80°C



- ◆ Double junction clearly visible after 8 min at 80°C
- ◆ After 960 min at 80°C "clear" type inversion

# $\Delta N_{\text{eff}}$ from CCE-V (TCT) and $C_s$ -V measurements

- proton irradiated oxygenated silicon -



- ◆ Open symbols: CCE-V values
- ◆ Filled symbols:  $C_s$ -V
- ◆  $\Delta N_{\text{eff}}$  (resp.  $V_{\text{dep}}$ ): Coincidence between  $C_s$ -V and CCE (TCT)


## Damage Parameters for standard and oxygen-enriched silicon

	Standard Silicon		Oxygen-enriched Silicon	
	Neutrons	Protons	Neutrons	Protons
$g_a$	$1.8 \times 10^{-2} \text{ cm}^{-1}$	-	$1.4 \times 10^{-2} \text{ cm}^{-1}$	-
$\tau_a(20^\circ\text{C})$	55 h	-	70 h	-
$g_c$	$1.5 \times 10^{-2} \text{ cm}^{-1}$	$1.9 \times 10^{-2} \text{ cm}^{-1}$	$2.0 \times 10^{-2} \text{ cm}^{-1}$	$5.3 \times 10^{-3} \text{ cm}^{-1}$
$N_{C0}/N_{eff0}$	0.70	-	0.45	1.0
$g_Y$	$5.2 \times 10^{-2} \text{ cm}^{-1}$	$6.6 \times 10^{-2} \text{ cm}^{-1}$	$4.8 \times 10^{-2} \text{ cm}^{-1}$	$2.3 \times 10^{-2} \text{ cm}^{-1}$ (*)
$\tau_Y(20^\circ\text{C})$	480 d	-	800 d	950 d


(\*) saturation value measured for  $\Phi_{eq} = 6 \cdot 10^{14} \text{ cm}^{-2}$

→ Simulation of LHC scenarios; Example: ATLAS Pixel layers

B-Layer (4cm)




1<sup>st</sup> Layer (10cm)



# Damage Projection – ATLAS Pixel Detector – B-Layer

- ◆ Radiation level for B-Layer :
  - $\Phi_{\text{eq}}(\text{year}) = 3.5 \times 10^{14} \text{ cm}^{-2}$  (full luminosity)  
 $> 85\%$  charged hadrons
- ◆ Three scenarios :
  - 1 year = 100 days beam (-7°C)
    - (1) 3 days 20°C and 14 days 17°C
    - (2) 30 days 20°C
    - (3) 60 days 20°C
  - Rest of the year: no beam (-7°C)



## Summary

- For mass application Silicon is and will remain the prime detector grade semiconductor
  - + Si: material & process technology based on large scale, commercial
    - + Rad. Hardness problem improved considerably by defect engineering
    - + LHC-ATLAS-B-layer shown to withstand 10<sup>4</sup> operation
    - + with even long maintenance periods
    - however: cooling necessary
- Other material of interest for specific applications
  - Diamond as the only non-Si monolithic semiconductor
    - + Rad. hard, ultra fast, small  $\epsilon$ , usable @ RT
    - Polycrystalline non ideal CCE, polarisation
  - Compound Semiconductors becoming interesting but except GaAs not beyond experimental stage
    - + Rad Hardness usually less than for monolithic semicond. (Anti-hole eff.)

# The ROSE collaboration

35 member groups from HEP and Semiconductor Physics  
+ associated major manufacturing companies

## Visit our web-site for...

... more information  
... status reports  
.....references,  
.... preprints, etc....

**<http://cern.ch/rd48>**

or/and

**Michael Moll (CERN-EP-MIC-SD) :** [Michael.Moll@cern.ch](mailto:Michael.Moll@cern.ch)

**Gunnar Lindström (University of Hamburg):** [Gunnar.Lindstroem@desy.de](mailto:Gunnar.Lindstroem@desy.de)

**Steve Watts (Brunel University):** [Stephen.Watts@brunel.ac.uk](mailto:Stephen.Watts@brunel.ac.uk)

