



## 2-D magnetic design of the 7.8 m dipole for SIS300

Massimo Sorbi, Giovanni Bellomo, Stefania Farinon

INFN Sez. di Milano & Genova and Milan University

GSI, 23 May 2007

M. Sorbi

### **Contents**:

- 1. Magnet parameters
- 2. Overview of the configuration
- 3. Effects of magnetization in field quality
- 4. Conclusions

#### Main parameters of the dipole (reference design)

MAIN	Value
Nominal field	<b>1.5-4.5</b> T
Ramp rate	<b>1.0 T/s</b>
Radius of curvature	66.667 m
Magnetic length	7.756 m
Bending angle	6 2/3 deg.
Coil aperture diameter	<b>100 mm</b>
Max operating temperature of LHe	4.7 K
Current sharing temperature	≥ 5.7 K
CONDUCTOR (@300 K)	
Strand number/cable	36
Critical current density in s.c. @ 4.2 K & 5 T	2700 A/mm <sup>2</sup>
Strand critical current @ 4.2 K & 5 T	515 A
Width	15.10 mm (bare conductor)
Short side	1.362 mm
Long side	1.598 mm

#### Main parameters of the dipole (reference design)

#### MAGNET CROSS SECTION

Field quality	$\pm 2^{*}10^{-4}$
Reference radius for field quality	35 mm ( <u>70</u> % Rm)
N. of layer	1
N. of block	3-4-5
Yoke inner radius	98 mm
Yoke outer radius	< 250 mm
N. of large holes in the yoke	2
Diameter of the yoke main holes	50-70 mm

Value

We explored many configurations, with the purpose to maximize the number of conductors in order to decrease the current density.

The main conclusions are:

- 3-blocks: NO ACCEPTABLE SOLUTIONS.
- 4-blocks: some solutions with 34 turns
- 4-blocks: one solution with 35 turns and <u>40 strands cable</u>. But not convenient for higher losses and for constructions worries.
- 5-blocks: no solutions with 35 turns and <u>36 strands cable</u>
- 5-blocks: solutions with 34 turns

GSI, 23 May 2007

### 5-blocks solution selected:



- Blocks are almost radial
- For the field quality, the solution is good and stable
- The temperature margin is the largest of all explored solutions

#### **5-blocks selected configuration:**

Block number	5
Turn number:	17-9-4-2-2
Current	8924 A
Bpeak (with self-field)	4.90 T
Bpeak / Bo	1.09
Temperature margin	0.99 K
Coil inner radius	50 mm
Yoke inner radius	98 mm



 $(\mu_r \text{ yoke} = \infty)$ 

#### Harmonics (units E-4) at ref. radius R=35 mm

b3	b5	b7	b9	b11	b13
0.10	0.10	0.40	0.48	0.95	-1.11

#### **Comments on the magnetic configuration:**

We are quite confident that this configuration has been well optimized to maximize the temperature margin; indeed the subdivision of conductors/blocks has been searched in order to decrease the <u>peak field</u>.

We had an informal review with Ezio Todesco (CERN), who recently has been working on general scale-law for practical superconducting dipole/quadrupole.

His comments confirm (and encourage) our convictions:

"I send you some comments on the design for GSI proposed by INFN. I use the notations given in the PRSTAB paper.

•*The parameter*  $\gamma$  (central field per unit of current density) <u>is in line</u> with the quantity of cable used (see Fig. 1).

•The parameter  $\lambda$  (peak field to central field) is <u>7% less</u> of what expected by a 72° sector coil with a wedge between 48° and 60°. For magnets with small w/r as in your case, <u>one</u> <u>expects around 1.15 (i.e. 15% more peak field than in the centre)</u>, <u>but you manage to</u> <u>get 1.08</u>. Please note that you managed to screw up my scaling law which was working very well in all cases!



GSI, 23 May 2007

M. Sorbi

•*I find a critical field of 6.5 T. This puts you at <u>69% of the loadline</u>, i.e. a margin of 31%. Usually magnets work with 20% margin, but here you have the losses.* 

•With respect to my scaling law, I find that you managed to <u>have 4.0% more in critical</u> <u>field</u> (compared to a case with the same quantity of cable), or <u>1.7% more in critical field</u> (compared to a case with the same width of cable, i.e. using a classical cross-section with 36 turns).

• Therefore, the comments I made in our meeting at CERN (try to increase the critical field putting more conductors) are wrong. <u>I think it is very well optimized</u>, <u>congratulations</u>."

(Ezio Todesco, private email, 18 April 2007)

#### **STORED ENERGY AND INDUCTANCE**

2D calculation	New design (Ø = 100 mm)	Old design (Ø = 92mm)
Stored energy / length	116.8 kJ/m	97 kJ/m
Inductance / length	2.9 mH/m	2.7 mH/m
Total energy (7.76 m)	0.90 MJ	0.76 MJ
Total inductance	22.5 mH	21.0 mH
Current ramp (@ $dB/dt = 1 T/s$ )	1980 A/s	1880 A/s
L dI/dt	45 V	40 V

#### **Magnetization effects**

- The main perturbation on b3 (and b5) due to magnetization of the materials are:
- 1. Persistent current in the s.c. filament
- 2. Inter-filament coupling current
- 3. Inter-strand coupling current
- 4. Paramagnetism of CuMn component of conductor
- 5. Magnetization and eddy current of beam tube
- 6. Magnetization of collar
- 7. Saturation effects of the iron yoke

#### 1. Persistent current & 2. inter filament coupling current.

It has been calculated with different approaches/codes. In all cases the magnetization of the strand has been calculated following the M.N. Wilson approach.

$$M_{w} = \frac{2}{3\pi} \lambda_{f} J_{c}(B) d_{f} + \frac{2}{\mu_{o}} \lambda_{fb} B_{i}' \tau(B) \qquad \tau = \frac{\mu_{o}}{2\rho_{t}(B)} \left(\frac{p}{2\pi}\right)$$

The different codes are:

- *Roxie* (a bit more sophisticated model for p.c.)
- Analytical *fortran code*
- Opera & Ansys with non-linear B-H curve for conductor
- Ansys with the description of current loops on each strand

# **3.** Inter strand coupling current via <u>adjacent</u> resistance and transverse field.

Calculated with:

- *Roxie* (Network modelization of Rutherford cable)
- Analytical *Excel code* (Wilson model)

(integration of the tranverse field  $B_t$  along the width of the conductor)

$$J_{z}(x) = \frac{p}{2R_{A}b \cdot c} \left( \int_{0}^{x} \dot{B} \, dx' - \frac{1}{2c} \int_{0}^{2c} dx'' \int_{0}^{x''} \dot{B} \, dx' \right)$$



GSI, 23 May 2007



# **3.** Inter strand coupling current via <u>crossover</u> resistance and coupling current via <u>adjacent</u> resistance in parallel field .

- Calculated only with *Roxie* (Network modelization of Rutherford cable)
- Not further investigated because negligible for field perturbation (also the losses are much lower than other contributions)

		F	P.C.	I.F.C	C.C.	I.S.C.	C. (Ra)
		δb3	$\delta$ b5	δb3	$\delta$ b5	δb3	$\delta b5$
	Roxie	-3.49	-0.37	-0.63	0.09	0.04	-0.15
B0 = 0.5 T	Opera	-3.67	-0.45	-0.63	0.08	-	-
	Fortran code	-3.65	-0.44	-0.63	0.1	-	-
	Excel code	-	-	-	-	0.03	-0.08
	Ansys dipole	-3.41	-0.55			-	-
	Ansys magn	-3.54	-0.38			-	-
	Roxie	-0.72	-0.09	-0.17	0.02	0.02 / 0.00	-0.05 / -0.04
B0 = 1.5 T	Opera	-0.72	-0.09	ok	ok	-	-
	Fortran code	-0.72	-0.09	-0.16	0.02	-	-
	Excel code	-	-	-	-	0.01	-0.03
	Ansys dipole	-0.70	-0.08			-	-
	Ansys magn	-0.74	-0.09			-	-
	Roxie	-0.25	-0.04	-0.06	0.01	0.01 / 0.00	-0.02 / -0.02
B0 = 3.0 T	Opera	-0.25	-0.04	ok	ok	-	-
	Fortran code	-0.25	-0.03	-0.06	0.01	-	-
	Excel code	-	-	-	-	0.00	-0.01
	Ansys dipole	-0.24	-0.05			-	-
	Ansys magn	-0.26	-0.04			-	-
	Roxie	-0.13	-0.02	-0.03	0	0.00 / 0.00	-0.02 / -0.01
B0 = 4.5 T	Opera	-0.13	-0.02	ok	ok	-	-
	Fortran code	-0.13	-0.02	-0.04	0	-	-
	Excel code	-	-	-	-	0.00	-0.01
	Ansys dipole	-0.12	-0.03			-	-
	Ansys magn	-0.14	-0.02			-	-

#### **Comparison between different codes**

GSI, 23 May 2007

**Summary of magnetization of conductor:** (missing CuMn paramagnetic effects)

- Acceleration mode (dB/dt = 1 T/s):

Central field	1.5 T	3.0 T	4.5 T
$\Delta b3$ (units)	-0.89	-0.31	-0.16

- Flat top (a) 4.5 T (dB/dt = 0)

 $\Delta b3 = -0.13$  units,  $\Delta bn < 0.02$  units (n=5,7,9,...)

- Stretcher mode (a) 0.5 T (dB/dt = 0)

 $\Delta b3 = -3.6$  units,  $\Delta b5 = -0.5$  units GSI, 23 May 2007

cable twist pitch	р	0.1	m
crossover resistance	Rc	2.00E-02	ohm
adjacent resistance	Ra	2.00E-04	ohm
number of strands	N	36	
radius of fil't boundary	a <sub>fb</sub>	0.3690	mm
matrix ratio	mat	1.800	
filament filling factor	λf	0.357	
wire trans res'y intercept	C <sub>pet</sub>	4.00E-10	ohm.m
wire trans res'y gradient	m <sub>pet</sub>	2.00E-10	ohm.m/T
wire twist pitch	p <sub>w</sub>	5.00E-03	m
filament diameter	d <sub>f</sub>	3.50E-06	m
cooking factors		1.00	

#### 4. Paramagnetism of CuMn matrix .

• By preliminary measurements, the paramagnetic component of CuMn has the approximate behaviour:



• The perturbation in the field quality is less than 1 unit:

Central field	1.5 T	3.0 T	4.5 T
$\Delta b3$ (units)	0.67	0.53	0.44
$\Delta b5$ (units)	-0.11	-0.10	-0.04

$$S_{CuMn}/S_{cond} = 0.18$$

GSI, 23 May 2007

M. Sorbi

#### **5.** Magnetization and eddy current in the beam tube.

• Analytical calculation gives zero contribution on harmonics (only very small dipole error  $b1 \approx -0.1$  unit)

Magnetization of beam tube

$$B_{inner} = B_0 \left[ 1 - \frac{(\mu_r - 1)^2}{4\mu_r} \left( 1 - \frac{r_{int}^2}{r_{ext}^2} \right) \right]$$

Eddy current in beam tube

$$J_{Z_{eddy}}(\vartheta) = -\frac{1}{\rho} \overset{\bullet}{B}_{0} r_{av} \cdot \cos(\vartheta)$$

• These results are confirmed by 2-D calculation with OPERA

(Warning: the LOSSES are not negligible!)

#### 6. Magnetization of collar



In order to keep the effect below 1 unit, it is necessary to use very qualified stainless steel (for example Nitronic 40).

#### 7. Saturation of the iron yoke

• The effect is strongly dependent on the real geometry and properties of the yoke:

- yoke outer radius
- ancillary holes (bus bars, etc.)
- actual geometry of the inner surface of yoke
- actual B-H curve of iron
- The harmonic variation between Bo=1.5 T-4.5 T is about:

 $\Delta b3 = -2$  units,  $\Delta b5 = -0.2$  units

• These perturbations can be corrected, **<u>but</u>** a more detailed definition of the above parameters is required.

#### Conclusions:

The proposed 5-blocks configuration with larger aperture has:

- Good field quality
- The perturbation on field quality due to magnetization of materials can be calculated with enough accuracy (according to <u>present</u> <u>models</u>), and all methods converge to the same results.
- Moderate harmonic perturbation during the ramp
- More informations are needed to complete the yoke cross section
- Some confirmation measurements for paramagnetism of CuMn should be given