

## **R&D** at **BNL**

### **GSI-INFN** Meeting

Nov. 13, 2007


J. Kaugerts

 Prepare standard R<sub>A</sub> measurement sample (rectangular cable stack) & determine preanneal time to get desired R<sub>A</sub> value in IHEP-built 6 T straight SIS 300 model dipole (inner layer cured twice, outer layer cured once)

 Prepare Ra measurement samples for curved sample holder, to determine sample geometry and pressure effects on Ra.
Vary azimuthal pressure on sample


• Use same (already measured at BNL) cable with EAS wire for all tests

### **BNL Curved Sample Holder**




Midplane block of the SIS 300 6 T straight dipole

#### **R**<sub>A</sub> after one RHIC-II cure cycle versus pre-anneal time




GSİ

#### R<sub>A</sub> after 1 & 2 RHIC-II cure cycles versus pre-anneal time



GSİ

### R<sub>A</sub> of 6 T straight SIS 300 model dipole




# Effect of room temperature pressure cycling on Ra straight sample

Pressure

at Measure- Ment (MPa)		Sample	Run #	Preann Temp, t (C)		Cycle type	Temp (C)	Pressure @ D (MPa)	Ra (μΩ)	+/-0	
	54	08287	2754	200	5.5	2 <sup>nd</sup> -II	195	34	208	11.3	
	54	08287	2756	200	5.5	2 <sup>nd</sup> -II-A	195	34	183.6	12.2	Thermal Cycle and pressure cycle (release, let sit, and then reapply)
	54	08287	2771	200	5.5	2 <sup>nd</sup> -II-B	195	34	242.4	21.3	Thermal Cycle and pressure cycle
	54	08287	2775	200	5.5	2 <sup>nd</sup> -II-C	195	34	303	28.4	Thermal Cycle and pressure cycle

# Effect of room temperature cycling on curved sample



Test pressures  $\sim$  70, 105, 35 MPa , successively applied

## Present Status of Testing

BNL (Arup Ghosh) plans to measure pressure on the sample yet with cryogenic strain gauges

### Conclusions

- Ra results are not very reproducible for samples from the same cable
- There appears to be a pressure dependence of Ra, i.e. decrease of Ra with increasing operational pressure inside the magnet coil
- Need to pre-anneal for at least 6 hours, to get Ra > 200  $\mu\Omega$
- Ra should be large enough so field quality is not affected by it and AC loss contribution is small. Then, it's variability will not matter